

BEFORE USE

Thank you for choosing M-System. Before use, please check contents of the package you received as outlined below.

If you have any problems or questions with the product, please contact M-System's Sales Office or representatives.

■ PACKAGE INCLUDES:

- Discrete input module.....(1)
- NeuronID label.....(2)

■ MODEL NO.

Confirm Model No. marking on the product to be exactly what you ordered.

■ INSTRUCTION MANUAL

This manual describes necessary points of caution when you use this product, including installation, connection and basic maintenance procedures.

LNS Plug-in Software (model: R7LPLG) is usable to set up Functional Blocks. For detailed information, refer to the R7PLG Users Manual. The R7LPLG is downloadable at M-System's web site: <http://www.m-system.co.jp>

POINTS OF CAUTION

■ POWER INPUT RATING & OPERATIONAL RANGE

- Locate the power input rating marked on the product and confirm its operational range as indicated below:
24V AC rating: 24V ±10%, 50/60 Hz, approx. 70mA
24V DC rating: 24V ±10%, approx. 40mA

■ GENERAL PRECAUTIONS

- The unit can acquire 16 points of discrete input, also pulse input can be acquired up to 8 points out of 16 points.
- When counter pulse and discrete are mixed and acquired, make sufficient consideration to them.
- Before you remove the unit or mount it, turn off the power supply and input signal for safety.

■ ENVIRONMENT

- Indoor use.
- When heavy dust or metal particles are present in the air, install the unit inside proper housing with sufficient ventilation.
- Do not install the unit where it is subjected to continuous vibration. Do not subject the unit to physical impact.
- Environmental temperature must be within -10 to +55°C (14 to 131°F) with relative humidity within 30 to 90% RH in order to ensure adequate life span and operation.

■ WIRING

- Do not install cables close to noise sources (relay drive cable, high frequency line, etc.).
- Do not bind these cables together with those in which noises are present. Do not install them in the same duct.


■ RESTRICTIONS WHEN USING LonMaker3.0 or 3.1

- Operating Environment
Please use LonMaker3.0 under the Environment of LNS3 Service Pack 8 and use LonMaker3.1 under the Environment of LonMaker3.1 Service Pack 3 or later.
Please use resource files of LonMark Resource File Ver12 or later.
- LNS Plug-in Software is not usable.
- The network variable of nvoCNTOut (fbCNT) is only SNVT_count_f.
- When registering a Device on LonMaker, please don't use the following items.
External Interface Definition / Upload From Device
Specify Device Channel / Auto-Detect

■ AND

- The unit is designed to function as soon as power is supplied, however, a warm up for 10 minutes is required for satisfying complete performance described in the data sheet.

COMPONENT IDENTIFICATION



■ STATUS INDICATOR LED

ID	COLOR	STATE	MEANING
PWR	Green	ON	Internal 5V is normal
		OFF	Internal 5V is abnormal.
ONLINE	Green	ON	Online
		Blink approx. 0.5 Hz	Offline Sending/receiving of Network Variables has stopped.
		Blink approx. 2 Hz	Receiving Wink Message
		OFF	Abnormal state
ERR	Red	ON	Writing in the non-volatile memory
		Blink	Abnormal state
		OFF	Normal state
TX/RX	Green	ON	Sending/receiving Network Variables
		OFF	Communication is lost.
SVCE	Green	ON	No network information
		Blink approx. 0.5 Hz	Offline Sending/receiving of Network Variables has stopped.
		OFF	Normal state

■ DISCRETE INPUT STATUS INDICATOR LED

Used to show discrete input signal status.

ON : LED ON
OFF : LED OFF

Note: For firmware version 0.14 or smaller, when the discrete inputs are commissioned by LonMaker, the LEDs indicate the status of them.

■ SERVICE SWITCH


Used to identify the node in LONWORKS network configuration.

■ RESET SWITCH

Used to reset the Neuron Chip. Press the switch behind the front cover to reset.

Control functions are halted while completing resetting and restarting. Confirm no danger before conducting resetting.


■ POWER SUPPLY, LONWORKS TERMINAL ASSIGNMENT



NO.	ID	FUNCTION, NOTES
1	NET1	LONWORKS communication 1
2	NET2	LONWORKS communication 2
3	FG	FG
4	NET1	LONWORKS communication 1
5	NET2	LONWORKS communication 2
6	U (+)	Power input
7	V (-)	Power input

Note: LONWORKS wiring must be paired between NET1 terminals and/or NET2 terminals.

■ INPUT TERMINAL ASSIGNMENT




NO.	ID	FUNCTION	NO.	ID	FUNCTION
1	COM	Common	10	NC	No Connection
2	X0	Input 0	11	X1	Input 1
3	X2	Input 2	12	X3	Input 3
4	X4	Input 4	13	X5	Input 5
5	X6	Input 6	14	X7	Input 7
6	X8	Input 8	15	X9	Input 9
7	XA	Input 10	16	XB	Input 11
8	XC	Input 12	17	XD	Input 13
9	XE	Input 14	18	XF	Input 15


TERMINAL CONNECTIONS

Connect the unit as in the diagram below.


EXTERNAL DIMENSIONS unit: mm (inch)



CONNECTION DIAGRAM




Input Connection Examples



COMMUNICATION CABLE CONNECTIONS

■ HOST PC CONNECTION



WIRING INSTRUCTIONS

■ SCREW TERMINAL


Torque: 0.5 N·m

■ SOLDERLESS TERMINAL

Refer to the drawing below for recommended ring tongue terminal size. Spade tongue type is also applicable.

Applicable wire size: 0.25 to 1.65 mm² (AWG 22 to 16)

Recommended manufacturer: Japan Solderless Terminal MFG. Co., Ltd, Nichifu Co., Ltd



DEVICE INTERFACE FILE


Device Interface File (XIF) is used to define a LONWORKS device when programmed on LonMaker. For this module, the following file is used:

R7L-DA16v113.XIF

The XIF files are downloadable at M-System's web site: <http://www.m-system.co.jp>

FUNCTIONAL BLOCKS

■ NodeObject




• Network Variables

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nviRequest	{SNVT_obj_request}	For use with LonMaker and other tools.
nvoStatus	{SNVT_obj_status}	For use with LonMaker and other tools.
nvoFileDirectory	{SNVT_address}	For use with LonMaker and other tools. Required to get access to Configuration Properties.
nvoABNLCond	{SNVT_state}	Shows the device status (All 0s in normal conditions). Bit 0 through Bit 9 : Invalid Bit 10 : E ² PROM Configuration Property check sum error Bit 11 : E ² PROM Count data check sum error (Bit 10 and Bit 11 can be reset to 0 by RQ_CLEAR_STATUS against NodeObject.) Bit 12 through Bit 15 : Invalid

• Configuration Properties

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTdirection	----	{SNVT_state} {0 or 1} {0,0,0,0,0,0,0,0, 0,0,0,0,0,0,0,0}	Bit 0, Bit 1: Setting the extension module (Power supply must be reset when this configuration property is changed.) 0,0 : Without extension module 1,0 : Discrete input (fb and other settings assigned to the 9th and following points are invalid with 8-point input module.) 0,1 : Discrete output (fb and other settings assigned to the 9th and following points are invalid with 8-point output module.) Set this property before an extension module is connected. Bit 2 through Bit 15 : Invalid
SCPTmaxSendTime [Number of fb]	----	{SNVT_time_sec} {0.0,10.0...3600.0} {0.0}	Maximum time interval to send network variables (per fb). (Power supply must be reset when this configuration property is changed.) Network variables are sent out in the specified intervals even when there is no change in the value. No sending when a value less than 10.0 is set. Invalid property when the assigned fb has no network variables to be sent to the network.
SCPTminSendTime [Number of fb]	----	{SNVT_time_sec} {0.0,0.2...3600.0} {1.0}	Minimum time interval to send network variables (per fb). (Power supply must be reset when this configuration property is changed.) Network variables are sent out in the specified intervals even when there are changes in the value faster than the interval. No sending when a value less than 0.2 is set. Invalid property when the assigned fb has no network variables to be sent to the network.
SCPTlocation	----	{SNVT_str_asc} {30-character string} {""}	Used to write Tag No. (name)
SCPToemType	----	{SNVT_str_asc} {e.g. "R7L-DA16_VER:0.10"}	Used to indicate Model No. and Version
SCPTserialNumber	----	{SNVT_str_asc} {e.g. "ZZ123456"}	Used to indicate Serial No.

■ FUNCTIONAL BLOCK: fbCNT [0...7]




• Network Variables

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nviCNTIn	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Counted object
nviCNTCtrl	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Controls operation of fbCNT 0.0 0 : Stop counting 100.0 1 : Start counting Invalid : Reset count value
nvoCNTOut	{SNVT_count_32} {0...999 999 999} {0} {SNVT_count_f} {0...999 999} {0}	Number of ON counts or accumulated time of ON status at nviCNTIn or the input terminal

• Configuration Properties

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTdirection	----	{SNVT_state} {0 or 1} {0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0}	<p>Bit 0 through 5: Counted object</p> <p>0,0,0,0,0,0 : nviCNTIn</p> <p>1,0,0,0,0,0 : X0 1,0,0,0,1,0 : ExX0</p> <p>0,1,0,0,0,0 : X1 0,1,0,0,1,0 : ExX1</p> <p>1,1,0,0,0,0 : X2 1,1,0,0,1,0 : ExX2</p> <p>0,0,1,0,0,0 : X3 0,0,1,0,1,0 : ExX3</p> <p>1,0,1,0,0,0 : X4 1,0,1,0,1,0 : ExX4</p> <p>0,1,1,0,0,0 : X5 0,1,1,0,1,0 : ExX5</p> <p>1,1,1,0,0,0 : X6 1,1,1,0,1,0 : ExX6</p> <p>0,0,0,1,0,0 : X7 0,0,0,1,1,0 : ExX7</p> <p>1,0,0,1,0,0 : X8 1,0,0,1,1,0 : ExX8</p> <p>0,1,0,1,0,0 : X9 0,1,0,1,1,0 : ExX9</p> <p>1,1,0,1,0,0 : XA 1,1,0,1,1,0 : ExXA</p> <p>0,0,1,1,0,0 : XB 0,0,1,1,1,0 : ExXB</p> <p>1,0,1,1,0,0 : XC 1,0,1,1,1,0 : ExXC</p> <p>0,1,1,1,0,0 : XD 0,1,1,1,1,0 : ExXD</p> <p>1,1,1,1,0,0 : XE 1,1,1,1,1,0 : ExXE</p> <p>0,0,0,0,1,0 : XF 0,0,0,0,0,1 : ExXF</p> <p>ExX0 through ExXF: Extension discrete input</p> <p>Bit 6: Count function</p> <p>0 : Number of status changes from OFF to ON</p> <p>1 : Accumulated time of ON status</p> <p>Bit 7: Memory storage at the non-volatile memory</p> <p>0 : Count retained in the memory and preset at the startup</p> <p>1 : Count always reset to 0</p> <p>Bit 8 through 15 : Invalid</p> <p>Minimum input pulse width 500 ms for nviCNTIn, 50 ms for the input terminals.</p> <p>DO NOT connect a network variable to nviCNTIn when one of the input terminals (other than nviCNTIn) is assigned as the counted object.</p> <p>ON time per 1 second increments.</p>
SCPTinvrtOut	nviCNTIn	{SNVT_lev_disc} {ST_OFF, ST_ON} {ST_OFF}	<p>Count logic at nviCNTIn.</p> <p>ST_OFF : Count with nviCNTIn = ON</p> <p>ST_ON : Count with nviCNTIn = OFF</p>
SCPTpwrUpState	nviCNTCtrl	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {100.0 1}	<p>Set value applied at nviCNTCtrl when the power supply is turned on.</p> <p>0.0 0 : Stop counting</p> <p>100.0 1 : Start counting</p> <p>Invalid : Reset count value</p>
SCPTnvType	nvoCNTOut	{SNVT_nv_type} {} {SNVT_count_f}	<p>Indicates nvoCNTOut type.</p> <p>For use with LonMaker and other tools.</p>
SCPTmaxRnge	nvoCNTOut	Same as nvoCNTOut. Default = Max. range value available for the type	<p>Maximum count for nvoCNTOut. Count reset to 0 and restarted at overflow.</p>
SCPTsetpoint	nvoCNTOut	Same as nvoCNTOut. Default = Max. range value available for the type	<p>Set value applied at nvoCNTOut when fbCNT[] is Over-Ride.</p>

■ FUNCTIONAL BLOCK: fbDI[0...7]



• Input Terminal v.s. fbDI Network Variables (nvoDIStat, nvoDIArm) Assignments

FUNCTIONAL BLOCK	NETWORK VARIABLE	OUTPUT TERMINAL
fbDI[0]	nvoDIStat	X0
	nvoDIArm	X1
fbDI[1]	nvoDIStat	X2
	nvoDIArm	X3
fbDI[2]	nvoDIStat	X4
	nvoDIArm	X5
fbDI[3]	nvoDIStat	X6
	nvoDIArm	X7
fbDI[4]	nvoDIStat	X8
	nvoDIArm	X9
fbDI[5]	nvoDIStat	XA
	nvoDIArm	XB
fbDI[6]	nvoDIStat	XC
	nvoDIArm	XD
fbDI[7]	nvoDIStat	XE
	nvoDIArm	XF

FUNCTIONAL BLOCK: fbDI[0...7]

• Network Variables

Normal Mode

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nvoDIStat	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Outputs X0, X2, X4, X6, X8, XA, XC, XE status
nvoDIArm	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Outputs X1, X3, X5, X7, X9, XB, XD, XF status

RS-Flip Flop Mode

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nvoDIStat	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	X0, X2, X4, X6, X8, XA, XC, XE : Set signal X1, X3, X5, X7, X9, XB, XD, XF : Reset signal When X0 or X1 receives an one-shot signal, fbDI data is set or reset respectively nvoDIStat outputs ON signal at Set. nvoDIArm outputs ON signal at Reset.
nvoDIArm	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	


Combination Mode

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS																																		
nvoDIStat	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	<p style="text-align: center;">Contact input, nvoDIStat and nvoDIArm Reference Table</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>X0</th> <th>X1</th> <th rowspan="2">nvoDIStat</th> <th rowspan="2">nvoDIArm</th> </tr> </thead> <tbody> <tr> <td>X2</td> <td>X3</td> </tr> <tr> <td>X4</td> <td>X5</td> </tr> <tr> <td>X6</td> <td>X7</td> </tr> <tr> <td>X8</td> <td>X9</td> </tr> <tr> <td>XA</td> <td>XB</td> </tr> <tr> <td>XC</td> <td>XD</td> </tr> <tr> <td>XE</td> <td>XF</td> </tr> <tr> <td>OFF</td> <td>OFF</td> <td>0.0 0 (OFF)</td> <td>Invalid</td> </tr> <tr> <td>ON</td> <td>OFF</td> <td>100.0 1 (ON)</td> <td>Invalid</td> </tr> <tr> <td>OFF</td> <td>ON</td> <td>0.0 0 (OFF)</td> <td>0.0 0 (OFF)</td> </tr> <tr> <td>ON</td> <td>ON</td> <td>100.0 1 (ON)</td> <td>100.0 1 (ON)</td> </tr> </tbody> </table>	X0	X1	nvoDIStat	nvoDIArm	X2	X3	X4	X5	X6	X7	X8	X9	XA	XB	XC	XD	XE	XF	OFF	OFF	0.0 0 (OFF)	Invalid	ON	OFF	100.0 1 (ON)	Invalid	OFF	ON	0.0 0 (OFF)	0.0 0 (OFF)	ON	ON	100.0 1 (ON)	100.0 1 (ON)
X0	X1		nvoDIStat	nvoDIArm																																
X2	X3																																			
X4	X5																																			
X6	X7																																			
X8	X9																																			
XA	XB																																			
XC	XD																																			
XE	XF																																			
OFF	OFF	0.0 0 (OFF)	Invalid																																	
ON	OFF	100.0 1 (ON)	Invalid																																	
OFF	ON	0.0 0 (OFF)	0.0 0 (OFF)																																	
ON	ON	100.0 1 (ON)	100.0 1 (ON)																																	
nvoDIArm	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}																																			

Configuration Properties

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTdirection	----	{SNVT_state} {0 or 1} {0,0,0,0,0,0,0,0, 0,0,0,0,0,0,0}	Bit 0, Bit 1: fbDI operating mode 0,0 : Normal mode 1,0 : RS-Flip Flop mode 0,1 : Combination mode Bit 2 through 15 : Invalid
SCPTinvrtOut	nvoDIStat	{SNVT_lev_disc} {ST_OFF, ST_ON} {ST_OFF}	Contact input logic is inverted at nvoDIStat. ST_OFF : OFF at open contact, ON at closed contact ST_ON : ON at open contact, OFF at closed contact
SCPTinvrtOut	nvoDIArm	{SNVT_lev_disc} {ST_OFF, ST_ON} {ST_OFF}	Contact input logic is inverted at nvoDIArm. ST_OFF : OFF at open contact, ON at closed contact ST_ON : ON at open contact, OFF at closed contact

■ FUNCTIONAL BLOCK: fbCMP[0...7]




• Network Variables

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nviCMPIn1	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Connects to the network variable to be compared.
nviCMPIn2	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Connects to the network variable to be compared.
nvoCMPOut	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	nviCMPIn1 and nviCMPIn2 are compared. OFF is output when both values are equivalent, ON or 'Invalid' is output when they are not. ON is output when nviCMPIn1 status change caused the discrepancy. 'Invalid' is output when nviCMPIn2 status change caused it. OFF is output when nviCMPIn1 and/or nviCMPIn2 is 'Invalid,' regardless of the values of both.

• Configuration Properties

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTtimeout	----	{SNVT_time_sec} {0.1...60.0} {5.0}	Delay time before ON or 'Invalid' is output when a discrepancy occurs between nviCMPIn1 and nviCMPIn2. OFF is immediately output when nviCMPIn1 and nviCMPIn2 states match, regardless of this setting.

■ FUNCTIONAL BLOCK: fbEN[0...3]



• Network Variables

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nviENIn1	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Encoder input 1
nviENIn2	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Encoder input 2
nviENIn3	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Encoder input 3
nviENIn4	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Encoder input 4
nvoENOut	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Outputs the SCPTvalueDefinition[] value according to the input signal status


• Configuration Properties

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTvalueDefinition[0...16]	----	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Table (below) defines output value against each input status

• Input v.s. SCPTvalueDefinition

nviENIn1	nviENIn2	nviENIn3	nviENIn4	nvoENOut VALUE
OFF	OFF	OFF	OFF	SCPTvalueDefinition[0]
ON	OFF	OFF	OFF	SCPTvalueDefinition[1]
OFF	ON	OFF	OFF	SCPTvalueDefinition[2]
ON	ON	OFF	OFF	SCPTvalueDefinition[3]
OFF	OFF	ON	OFF	SCPTvalueDefinition[4]
ON	OFF	ON	OFF	SCPTvalueDefinition[5]
OFF	ON	ON	OFF	SCPTvalueDefinition[6]
ON	ON	ON	OFF	SCPTvalueDefinition[7]
OFF	OFF	OFF	ON	SCPTvalueDefinition[8]
ON	OFF	OFF	ON	SCPTvalueDefinition[9]
ON	ON	OFF	ON	SCPTvalueDefinition[10]
OFF	ON	OFF	ON	SCPTvalueDefinition[11]
ON	OFF	ON	ON	SCPTvalueDefinition[12]
OFF	OFF	ON	ON	SCPTvalueDefinition[13]
ON	ON	ON	ON	SCPTvalueDefinition[14]
OFF	ON	ON	ON	SCPTvalueDefinition[15]
Invalid in one or more nviENIn				SCPTvalueDefinition[16]

■ FUNCTIONAL BLOCK: fbTMR[0,1]



• Network Variables

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nviTMRIn	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Starts the timer function. With 'Invalid,' nvoTMROut is reset to the default status and the internal counter is reset.
nvoTMROut	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Timer output

• Configuration Properties

Common

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTdirection	----	{SNVT_state} {0 or 1} {0,0,0,0,0,0,0,0, 0,0,0,0,0,0,0,0}	Bit 0 : fbTMR operating mode 0 : One shot mode 1 : Cyclic mode Bit 1 through 15 : Invalid
SCPTinvrtOut	nviTMRIn	{SNVT_lev_disc} {ST_OFF, ST_ON} {ST_OFF}	Timer's trigger condition ST_OFF : Start with nviTMRIn = ON, Stop at OFF ST_ON : Start with nviTMRIn = OFF, Stop at ON
SCPTinvtOut	nvoTMROut	{SNVT_lev_disc} {ST_OFF, ST_ON} {ST_OFF}	Inverts the timer output logic. ST_OFF : nvoTMROut = ON with the timer functioning and ON, nvoTMROut = OFF in any other conditions. ST_ON : nvoTMROut = OFF with the timer functioning and ON, nvoTMROut = ON in any other conditions.

One Shot Mode

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTtimeout[0]	----	{SNVT_time_sec} {0.0...800.0} {10.0}	Delay time before nvoTMROut is turned on after nviTMRIn has been turned on.
SCPTtimeout[1]	----	{SNVT_time_sec} {1.0...800.0,800.1} {10.0}	Time to maintain ON status of nvoTMROut after it has been turned on. 800.1 = Latching (no turning off)
SCPTtimeout[2]	----	{SNVT_time_sec} {0.0...800.0,800.1} {10.0}	Delay time before nvoTMROut is turned off after nviTMRIn has been turned off. 800.1 = Latching (no turning off) (With SCPTtimeout[1] also set to '800.1,' nvoTMROut remains on. Set 'Invalid' at nviTMRIn to turn nvoTMROut off.

[Example]


- Providing one-shot output when nviTMRIn is turned on:
 - SCPTtimeout[0] : One-shot output delay time
 - SCPTtimeout[1] : Pulse width
 - SCPTtimeout[2] : 800.1* (Holds nvoTMROut when nviTMRIn is turned off.)
- * If SCPTtimeout[2] equals other than 800.1, the pulse width equals the addition of SCPTtimeout[1] and SCPTtimeout[2].
- Turning nvoTMROut on in a specific time period after nviTMRIn is turned on:
 - SCPTtimeout[0] : ON delay time
 - SCPTtimeout[1] : 800.1 (Holds nvoTMROut on while nviTMRIn remains on.)
 - SCPTtimeout[2] : Time to hold nvoTMROut on after nviTMRIn is turned off.

Cyclic Mode

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTtimeout[0]	----	{SNVT_time_sec} {0.0} {0.0}	Invalid
SCPTtimeout[1]	----	{SNVT_time_sec} {0.0...800.0} {0.0}	Defines ON-OFF time period. ON and OFF times are equal. One pulse cycle equals twice as long as the set value.
SCPTtimeout[2]	----	{SNVT_time_sec} {0.0} {0.0}	Invalid

■ FUNCTIONAL BLOCK: fbDOEX[0...7]

This Functional Block is valid only when the output extension module is specified at NodeObject.



• Output Terminal v.s. fbDOEX Network Variables (nviDOEX1, nviDOEX2) Assignments

FUNCTIONAL BLOCK	NETWORK VARIABLE	OUTPUT TERMINAL
fbDOEX[0]	nviDOEX1	Y0
	nviDOEX2	Y1
fbDOEX[1]	nviDOEX1	Y2
	nviDOEX2	Y3
fbDOEX[2]	nviDOEX1	Y4
	nviDOEX2	Y5
fbDOEX[3]	nviDOEX1	Y6
	nviDOEX2	Y7
fbDOEX[4]	nviDOEX1	Y8
	nviDOEX2	Y9
fbDOEX[5]	nviDOEX1	YA
	nviDOEX2	YB
fbDOEX[6]	nviDOEX1	YC
	nviDOEX2	YD
fbDOEX[7]	nviDOEX1	YE
	nviDOEX2	YF

■ FUNCTIONAL BLOCK: fbDOEX[0...7]

• Network Properties


NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nviDOEX1	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Turns on or off Y0, Y2, Y4, Y6, Y8, YA, YC, YE of the extension module depending upon this input. 100.0 1 : ON Other : OFF
nviDOEX2	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Turns on or off Y1, Y3, Y5, Y7, Y9, YB, YD, YF of the extension module depending upon this input. 100.0 1 : ON Other : OFF

• Configuration Properties

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTdirection	----	{SNVT_state} {0 or 1} {0,0,0,0,0,0,0,0, 0,0,0,0,0,0,0}	Bit 1: Output held or not at power off 0 : OFF at the power startup 1 : Outputs the held status at the power startup Bit 0, Bit 2 through 15 : Invalid
SCPTpwrUpState	nviDOEX1	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Set value applied at nviDOEX1 when the power supply is turned on.
SCPTpwrUpState	nviDOEX2	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Set value applied at nviDOEX2 when the power supply is turned on.

■ FUNCTIONAL BLOCK: fbDIEX[0...7]

This Functional Block is valid only when the input extension module is specified at NodeObject.



• Input Terminal v.s. fbDIEX Network Variables (nvoDIEX1, nvoDIEX2) Assignments

FUNCTIONAL BLOCK	NETWORK VARIABLE	INPUT TERMINAL
fbDIEX[0]	nvoDIEX1	X0
	nvoDIEX2	X1
fbDIEX[1]	nvoDIEX1	X2
	nvoDIEX2	X3
fbDIEX[2]	nvoDIEX1	X4
	nvoDIEX2	X5
fbDIEX[3]	nvoDIEX1	X6
	nvoDIEX2	X7
fbDIEX[4]	nvoDIEX1	X8
	nvoDIEX2	X9
fbDIEX[5]	nvoDIEX1	XA
	nvoDIEX2	XB
fbDIEX[6]	nvoDIEX1	XC
	nvoDIEX2	XD
fbDIEX[7]	nvoDIEX1	XE
	nvoDIEX2	XF

■ FUNCTIONAL BLOCK: fbDIEX[0...7]

• Network Variables

Normal Mode

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
nvoDIEX1	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Outputs X0, X2, X4, X6, X8, XA, XC, XE status of the extension module
nvoDIEX2	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Outputs X1, X3, X5, X7, X9, XB, XD, XF status of the extension module

Combination Mode

NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS																																														
nvoDIEX1	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}	Contact input, nvoDIEX1 and nvoDIEX2 Reference Table <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>X0</th> <th>X1</th> <th rowspan="2">nvoDIEX1</th> <th rowspan="2">nvoDIEX2</th> </tr> <tr> <th>X2</th> <th>X3</th> </tr> </thead> <tbody> <tr> <td>X4</td> <td>X5</td> <td></td> <td></td> </tr> <tr> <td>X6</td> <td>X7</td> <td></td> <td></td> </tr> <tr> <td>X8</td> <td>X9</td> <td></td> <td></td> </tr> <tr> <td>XA</td> <td>XB</td> <td></td> <td></td> </tr> <tr> <td>XC</td> <td>XD</td> <td></td> <td></td> </tr> <tr> <td>XE</td> <td>XF</td> <td></td> <td></td> </tr> <tr> <td>OFF</td> <td>OFF</td> <td>0.0 0 (OFF)</td> <td>Invalid</td> </tr> <tr> <td>ON</td> <td>OFF</td> <td>100.0 1 (ON)</td> <td>Invalid</td> </tr> <tr> <td>OFF</td> <td>ON</td> <td>0.0 0 (OFF)</td> <td>0.0 0 (OFF)</td> </tr> <tr> <td>ON</td> <td>ON</td> <td>100.0 1 (ON)</td> <td>100.0 1 (ON)</td> </tr> </tbody> </table>	X0	X1	nvoDIEX1	nvoDIEX2	X2	X3	X4	X5			X6	X7			X8	X9			XA	XB			XC	XD			XE	XF			OFF	OFF	0.0 0 (OFF)	Invalid	ON	OFF	100.0 1 (ON)	Invalid	OFF	ON	0.0 0 (OFF)	0.0 0 (OFF)	ON	ON	100.0 1 (ON)	100.0 1 (ON)
X0	X1		nvoDIEX1	nvoDIEX2																																												
X2	X3																																															
X4	X5																																															
X6	X7																																															
X8	X9																																															
XA	XB																																															
XC	XD																																															
XE	XF																																															
OFF	OFF	0.0 0 (OFF)	Invalid																																													
ON	OFF	100.0 1 (ON)	Invalid																																													
OFF	ON	0.0 0 (OFF)	0.0 0 (OFF)																																													
ON	ON	100.0 1 (ON)	100.0 1 (ON)																																													
nvoDIEX2	{SNVT_switch} {0.0 0}, {100.0 1}, {Invalid} {0.0 0}																																															

• Configuration Properties

CONFIGURATION PROPERTY	NETWORK VARIABLE	TYPE { Range } { Default }	EXPLANATIONS
SCPTdirection	----	{SNVT_state} {0 or 1} {0,0,0,0,0,0,0,0, 0,0,0,0,0,0,0}	Bit 0, Bit 1: fbDIEX operating mode 0,0 : Normal mode 0,1 : Combination mode Bit 2 through 15 : Invalid
SCPTinvtOut	nvoDIEX1	{SNVT_lev_disc} {ST_OFF, ST_ON} {ST_OFF}	Contact input logic is inverted at nvoDIEX1. ST_OFF : OFF at open contact, ON at closed contact ST_ON : ON at open contact, OFF at closed contact
SCPTinvtOut	nvoDIEX2	{SNVT_lev_disc} {ST_OFF, ST_ON} {ST_OFF}	Contact input logic is inverted at nvoDIEX2. ST_OFF : OFF at open contact, ON at closed contact ST_ON : ON at open contact, OFF at closed contact